## NAME VR-H2009-230 Electrical Specification VR-1-1-1970 NO **Regulator Features : Regulation System Connection Wire Diagram** •Regulation : A – Circuit •Stand by mode& Leakage LIN (COM) **Dummy** current control • Self mode **GND** • Default mode • LIN (Com) mode B+ • 19200&9600Baud Rate(4byte) PS • Variable V setting **F** (BOTTOM) • Field out duty monitor • Temperature & Field current

Parameters and Conditions	SPEC	Min.	Туре	Max.	SYMBOLS
Switch OFF Leakage Current	PS < 800rpm , LIN = Low , B+=12.0V			1	mA
	Default Mode	14.0	14.2	14.4	V
Regulator Set Point	Defined by external ECU/LIN command.	10.7		16.0	V
Output Saturation Voltage	I F = 5A			0.8	V
Field Current Limit	F shorted to ground		12	14	Α
Field Control Frequency	10% < Duty cycle < 95%	150	200	250	Hz
Error Display High Temp. Protection Threshold on Board (Substrate)	Field output OFF		160		ĉ
Self Drive Termination RPM Threshold Safe mode	Safe mode	725	800	875	rpm
Self Drive Initiation RPM Threshold	Safe mode frequency given according to the programmed number of generator poles	3350	3800	4250	rpm

**Safety Characteristics:** 

> Over voltage : Vs = 24 V, 60 sec. from the ignition SW. is turned ON/OFF without failure.

Short Circuit Protection : The regulator shall stand short circuit on Field without failure and return normal operation within 2 seconds once short condition is removed.

Repetitive Thermal Shock : The Regulator shall be designed to withstand 500 cycles of -30°C to 125°C in 20 minutes and 125°C to -30°C in 20 minutes.

➤ High Temperature Test : The regulator shall be designed to operate reliably at the load from 80% to 100% of the alternator rated current and at 6000 rpm ( shaft speed ) for a minimum of 10 hours at 125°C.

2019.11.06		1	廖建榮	陳建文	陳建文	MOBILETRON
Date of Date of		Manu-	Review		Nov.11.2019	
first edition	revised Edition script Review Approval	Approva	Approval	Release		