VR-B3025 Electrical Specification

NO

VR-1-1-2555

Regulation System Connection Wire Diagram LIN F(top) GND

Regulator Features:

- Voltage Set Point : 14.3V (Default Vset)
- Regulation : B Circuit
- Standby mode
- Leakage current control
- Safe mode
- Default mode
- LIN (Com) mode
- 9600/19200 Baud rate (4byte)
- Variable V setting
- Field out duty monitor
- Temperature & Field current

PARAMETERS AND CONDITIONS	SPEC	Min.	Type Max.		SYMBOLS
Operating Temperature	Operating Temperature	-30		125	င
Switch OFF Leakage Current	Ps < 800rpm , LIN= Low , B+=12.0V 2.0				
	Default Mode	14.1	14.3	14.5	V
Regulator Set Point	Defined by external ECU/LIN command.	10.6		16.0	V
Output Saturation Voltage	I F = 5A			0.5	V
Field Current Limit	F shorted to B+	8		12	A
Field Control Frequency	10% < duty cycle < 95%		220		Hz
Error Display High Temp. Protection Threshold on board(substrate)	Field output OFF		160		c
Self Drive Initiation rpm Threshold	Safe mode Frequency given according to the programmed number of generator poles	2450	3000	3550	rpm

Safety Characteristics:

- Over voltage: Vs = 24 V, 60 sec. from the ignition SW. is turned ON/OFF without failure.
 Short Circuit Protection: The regulator shall stand short circuit on Field without failure and return normal operation within 2 seconds once short condition is removed.
- ➤ Repetitive Thermal Shock: The Regulator shall be designed to withstand 500 cycles of -30°C to 125°C in $\hat{2}0$ minutes and $125^{\circ}\mathbb{C}$ to $-30^{\circ}\mathbb{C}$ in $\hat{2}0$ minutes.
- ➤ High Temperature Test: The regulator shall be designed to operate reliably at the load from 80% to 100% of the alternator rated current and at 6000 rpm (shaft speed) for a minimum of 10 hours at 125°C.

2024.10.30		1	賴佑昇	柯文彬	林勝雄	林勝雄		
DATE OF FIRST EDITION	REVISED	EDITION	SCRIPT	CINIAI	SECOND REVIEW	APP- ROVAL	ISSUED MARK	COPY'S NUMBER

[CBP-020012]